

SWISSONOR HISTORIC 8910 MONO PHONO STAGE



**UNCOMPROMISING SOUND
IN COUNTLESS COMBINATIONS
FOR ALL RECORDS SINCE 1889**

THIS VERSATILE MONO PHONO PREAMPLIFIER IS AIMED AT THE DISCERNING MUSIC LOVER.

RECORDS FROM ALL ERAS, INCLUDING SHELLAC RECORDS, CAN BE CORRECTED HISTORICALLY AND MUSICALLY IN A SIMPLE WAY.

THE DEVICE CAN BE USED IN A WIDE VARIETY OF CONFIGURATIONS AND ADAPTED TO A VARIETY OF PLAYBACK SYSTEMS.

THE HISTORIC 8910 MEETS THE HIGHEST EXPECTATIONS IN RESPECT TO OBJECTIVE AND SUBJECTIVE REPRODUCTION QUALITY, AND THUS ELEVATES YOUR CURRENT AND FUTURE LP COLLECTION TO NEW HEIGHTS.

THE AMPLIFIER STAGES ARE DIRECTLY COUPLED, THE EQUALIZATION IS PASSIVE. SIGNAL PATHS ARE EXTREMELY SHORT, AND THE TWO HIGH-LEVEL OUTPUTS ARE WIRED DIRECTLY.

THE EXTERNAL 24 V POWER SUPPLY UNIT IS INTERNALLY INDUCTIVELY AND CAPACITIVELY DECOUPLED. ALSO THE MECHANICAL CONSTRUCTION IS OF CORRESPONDING QUALITY WITH A CAST CHASSIS, AND THE ALUMINUM FRONT PANEL IS MOUNTED ON SILENT BLOCKS ... ALL TO THE HIGH SWISSONOR STANDARD.

RECOMMENDED CONFIGURATIONS :

- A HISTORIC 8910 PARALLEL TO AN EXISTING RIAA STEREO PHONO PREAMPLIFIER, FOR PLAYBACK OF ALL MONOPHONIC RECORDS ON MONO AND STEREOS
- TWO HISTORIC 8910 ADVANTAGEOUSLY REPLACE A STEREO PHONO PREAMPLIFIER FOR ALL APPLICATIONS.
- FOR TRANSFERRING RECORDS TO MODERN SOUND CARRIERS

SPECIFICATIONS :

LOW OUTPUT MC INPUT :

- INPUT SENSITIVITY 0.2 / 0.3 / 0.5 MV * WITH JUMPER
- INPUT IMPEDANCE 20 / 47/200 OHM WITH JUMPER

HIGH OUTPUT MC / MM INPUT :

- INPUT SENSITIVITY 2 / 3 / 4.5 MV * WITH JUMPER
- INPUT IMPEDANCE 1 / 4.7 / 47 KOHM WITH JUMPER
- INPUT CAPACITY 100 / 200/320 PF WITH JUMPER

CHARACTERISTIC CURVES THAT CAN BE SELECTED USING A ROTARY SWITCH, 100%
PASSIVE RC CORRECTION NETWORKS :

- RIAA 1955 FOR ALL RECORDS FROM 1956
- COLUMBIA LP E.G. FOR COLUMBIA, WESTMINSTER
- AES 1951 E.G. FOR PHILIPS, MERCURY, RCA
- CCIR-DIN E.G. FOR DEUTSCHE GRAMMOPHON
- ACOUSTICS CYLINDERS AND SHELLAC BEFORE 1925
- BLUMLEIN SHELLAC AND VINYL 1925 TO 1955:

BLUMLEIN 500 HZ

BLUMLEIN 400 HZ

BLUMLEIN 350 HZ

BLUMLEIN 300 HZ

BLUMLEIN 250 HZ

BLUMLEIN 200 HZ

A TABLE PROVIDED MAKES IT EASY TO CHOOSE THE RIGHT EQUALIZATION

2 LINE LEVEL OUTPUTS, SUITABLE FOR BOTH ACTIVE AND PASSIVE
PREAMPLIFIERS :

- OUTPUT GAIN 26, 29, 32 DB WITH JUMPER
- OUTPUT IMPEDANCE 150 OHM
- STANDARD LENGTH OF THE OUTPUT CABLE 2X 1.5 M,
OTHERS ON REQUEST

* TOTAL GAIN (1 KHZ) : 32 TO 72 DB IN 27 LEVELS ALLOWS THE OPTIMAL GAIN
FOR EALL MM AND MC CARTRIDGES.

MADE BY HAND IN SWITZERLAND

PRESENTED BY YOUR SWISSONOR SPECIALIST DEALER :

ATELIER 13 AUDIO
NAHVILLE TN
(615) 881 0427
www.atelier13-usa.com